

Nr	Nazwa rozdzielnicy	P <sub>i</sub>	k	P <sub>s</sub>	cosf	I <sub>B</sub>	I <sub>N</sub>	typ kabla	przekrój	przewodność	RI	XI	I <sub>z</sub>	k <sub>g</sub>	I <sub>z</sub> k <sub>g</sub>	L	dU	kl <sub>2</sub>	I <sub>2</sub>	1,45xI <sub>z</sub>	I <sub>B</sub> <I <sub>N</sub> <I <sub>z</sub>	I <sub>2</sub> <1,45xI <sub>z</sub>
		[kW]	[-]	[kW]	[-]	[A]	[A]	[-]	[mm <sup>2</sup> ]	[S/mm <sup>2</sup> ]	[mΩ]	[mΩ]	[A]		[A]	[m]	[%]	[-]	[A]	[A]	[TAK/NIE]	[TAK/NIE]
1	Zasilanie podstawowe	729,0	0,65	472,0	0,88	774,2	1000	4x 5xYAKXS 1x240	1 150	34	4,48	17,50	1 360	1,00	1 360,0	175	4,11	1,45	1 450,0	1 972,0	TAK	TAK
2	Zasilanie rezerwowe	242,0	0,6	142	0,88	232,9	400	4x 2xYAKXS 1x240	480	34	9,19	15,00	544	0,86	467,8	150	1,53	1,45	580,0	678,4	TAK	TAK